



Roger Select is a versatile microphone ideal for stationary situations where background noise is present. When placed on a table, it discreetly and automatically selects the person who is talking and seamlessly switches from one talker to another. When multiple conversations take place, the listener can manually select whom to listen to. It can also transmit sound the sound of multimedia devices e.g. T.V. and has Bluetooth® for phone calls.



- 1) On/off button incl. battery status light
- 2) Microphones and center indicator lights
- 3) Center touch key
- 4) Six steering touch keys
- 5) Microphone mode indicator lights



- 6) Bluetooth button
- 7) Back indicator light
- 8) Connect button
- 9) Micro-USB socket
- 10) Slots for lanyard and clip

#### Roger Select features

- Proven Roger speech-in-noise performance
- MultiBeam Technology
- Table mode
- Selection mode

- Lapel mode
- Audio input for multimedia
- Bluetooth® for phone calls
- Multiple microphone use in a network (MultiTalker Network)

#### General information

Dimensions (Ø x H):

Weight:

Color options:

Included accessories:

Coperating conditions:

Dimensions (Ø x H):

28 g / 0.99 oz

Champagne, Pearl White, Graphite Gray

Power Supply with USB cable, Docking Station, optical audio cable, Clip,

Lanyard, Pouch

Operating conditions:

O°C to 40°C (+32°F to +104°F). Relative humidity of <90%

(non-condensing)

Transport and storage conditions:

-20°C to 60°C (-4°F to +140°F). Relative humidity of <90% for a long period of time



### Power supply

Type:	DC, stabilized
Primary voltage:	100 - 240 V
Secondary voltage:	5 VDC
Max. current:	1.0 A
Plug:	micro-USB
Important notice:	Only use the original USB Phonak power

5 VDC, > 500 mA

supply

#### **Battery**

Lithium Polymer
400 mAh
3.7 V
8 hours

#### Audio information

Audio input:	Analog via micro-USB socket
Audio bandwidth:	100 Hz – 7.3 kHz

## Microphone characteristics

Number of Microphones:	3
Microphone modes:	Table mode, Selection mode, Lapel mode

### Radio information

Roger technology
2.4 GHz ISM band including adaptive automatic frequency hopping
100 mW max.
10 meters / 33 feet (typical) 20 meters / 66 feet (ideal conditions)

### **Docking station**



Audio input (3.5 mm socket):

- Analog

- Digital optical (Toslink)

### Receiver compatibility

Compatible Roger receivers:  Max. connected receivers:	All Roger receivers , except SoundField receivers
	Unlimited

# Microphone compatibility (MultiTalker Network)

A Roger Select in a MultiTalker Network functions only in lapel mode (hanging around the neck or clipped on the chest).

Compatible	Roger™ Table Mic II
microphones:	Roger Select™
	Roger Pen™
	Roger™ EasyPen
	Roger™ Clip-On Mic
Max. connected	Up to 10

#### **Standards**

Bluetooth range:

Europe	EN 300 328
	EN 301 489
	EN 62368-1
	IEC/EN 62311
Canada	RSS-247
	RSS-102
Japan	ARIB-T66
USA	CFR 47, part 15.247
	FCC OET Bulletin No.65

## Bluetooth for phone calls

Bluetooth	Headset Profile (HSP)
profiles supported:	Handsfree Profile (HFP)
Bluetooth compliance:	Bluetooth version 4.0
Max. paired phones:	8
Max. connected phones:	2

3 meters / 10 feet (Class 2)



The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by Phonak is under license. Other trademarks and trade names are those of their respective owners.